

Programming Caller ID Name on SBX

Category: PBX Configuration

Program the lines and stations using the following settings:

<u>PGM</u>	<u>BTN</u>	<u>Description</u>	<u>Setting</u>
147	1	CID Mode	1:FSK
147	2	CID Name Display	1:NAME
114	1	CLIP display	1:ON

This will result in displaying both CallerID number and name on lines that provide both values on an incoming call.

Example:

Program Caller ID via Phone Admin for CO lines 1-3 and stations 100-107:

1. Log into system programming from Station 100
2. Press **PGM** and dial **147**
3. Dial **0103** (CO Range to program)
4. Press **Flex Button 1**
5. Dial **1** (FSK)
6. **Save**
7. Press **Flex Button 2** and dial **1** (NAME)
8. **Save**
9. Press **PGM** and dial **114**
10. Dial **100107** (the Station Range to Program)
11. Press **Flex Button 1** and dial **1** (turn on Caller ID Display)
12. **Save**